
HINKLEY
LIGHTING


# assembly instructions

2132

Family: Rowe Park | Item No. 2132



**Drawing 1 - Fixture Assembly**




## start here

**1**

**1.** Find a clear area in which you can work.

**2.** Unpack fixture and glass from carton.

**3.** Carefully review instructions prior to assembly.

****** The construction of this fixture will be accomplished by first assembling the fixture, installing the mounting bracket to the junction box, making all necessary electrical connections, and hanging the fixture from the ceiling.***

**SAFETY WARNING: READ WIRING AND GROUNDING INSTRUCTIONS (I.S. 18) AND ANY ADDITIONAL DIRECTIONS. TURN POWER SUPPLY OFF DURING INSTALLATION. IF NEW WIRING IS REQUIRED, CONSULT A QUALIFIED ELECTRICIAN OR LOCAL AUTHORITIES FOR CODE REQUIREMENTS.**

**2**

**1.** To assemble fixture, slip center stem **(2)** along wire and thread into coupler **(7)**, located at top of cage assembly **(1)**, approximately 3/8".

**2.** Thread hex nut **(6)** down center stem **(2)** and tighten against coupler **(7)**.

**3.** Slip cap **(3)** along wire and onto center stem **(2)**.

**4.** Slip decorative knob **(4)** along wire and onto center stem **(2)**.

**5.** Slip loop **(5)** along wire and thread onto end of center stem **(2)** and tighten.

**6.** Please refer to the hanging instruction sheet **(I.S. 19)** provided to hang this fixture. Then fixture can be lamped accordingly.

10.16.09


HINKLEY
LIGHTING

# I.S. 18 wiring | grounding instructions




**SAFETY WARNING: READ WIRING AND GROUNDING INSTRUCTIONS (I.S. 18) AND ANY ADDITIONAL DIRECTIONS. TURN POWER SUPPLY OFF DURING INSTALLATION. IF NEW WIRING IS REQUIRED, CONSULT A QUALIFIED ELECTRICIAN OR LOCAL AUTHORITIES FOR CODE REQUIREMENTS.**


**Drawing 1 - Flush Mount**




**Drawing 2 - Chain Hung**




**Drawing 3 - Post-Mount**




## wiring instructions

**Indoor Fixtures**

**1.** Connect positive supply wire **(A)** (typically black or the smooth, unmarked side of the two-conductor cord) to positive fixture lead **(B)** with appropriately sized twist on connector - see **Drawings 1 or 2**.

**2.** Connect negative supply wire **(C)** (typically white or the ribbed, marked side of the two-conductor cord) to negative fixture lead **(D)**.

**3.** Please refer to the **grounding instructions** below to complete all electrical connections.

**Outdoor Fixtures**

**1.** Connect positive supply wire **(A)** (typically black or the smooth unmarked side of the two-conductor cord) to positive fixture lead **(B)** with appropriately sized twist on connector - see **Drawings 2 or 3**.

**2.** Connect negative supply wire **(C)** (typically white or the ribbed, marked side of the two-conductor cord) to negative fixture lead **(D)**.

**3.** Cover open end of connectors with silicone sealant to form a watertight seal.

• If installing a wall mount fixture, use caulk to seal gaps between the fixture mounting plate (backplate) and the wall. This will help prevent water from entering the outlet box. If the wall surface is lap siding, use caulk and a fixture mounting platform specially.

**4.** Please refer to the **grounding instructions** below to complete all electrical connections.

## grounding instructions

**Flush Mount Fixtures**
For positive grounding in a 3-wire electrical system, fasten the fixture ground wire **(E)** (typically copper or green plastic coated) to the fixture mounting strap **(1)** with the ground screw **(2)** - see **Drawing 1**.
Note: On straps for screw supported fixtures, first install the two mounting screws in strap. Any remaining tapped hole may be used for the ground screw.

**Chain Hung Fixtures**
Loop fixture ground wire **(E)** (typically copper or green plastic coated) under the head of the ground screw **(2)** on fixture mounting strap **(1)** and connect to the loose end of the fixture ground wire directly to the ground wire of the building system with appropriately sized twist-on connectors - see **Drawing 2**.

**Post-Mount Fixtures**
Connect fixture ground wire **(E)** (typically copper or green plastic coated) to power supply ground with appropriately sized twist-on connector inside post. Cover open end of connector with silicone sealant to form a watertight seal - see **Drawing 3**.